



# Mac Mini Late 2014 Antenna Plate Replacement

Remove or replace the antenna plate on a Mac Mini Late 2014.

Written By: Sam Lionheart



## INTRODUCTION

Use this guide to replace the metal antenna plate in your Mac Mini Late 2014.



### TOOLS:

- [iFixit Opening Tools](#) (1)
- [TR6 Torx Security Screwdriver](#) (1)
- [Spudger](#) (1)



### PARTS:

- [Mac mini A1347 \(Late 2014\) Antenna Plate](#) (1)
-

## Step 1 — Bottom Cover



- The bottom cover is clipped onto three screw posts.
- Pry near, but not right on the screw posts.

## Step 2



- Use the plastic opening tool to pry the bottom cover up off of the Mac Mini.

### Step 3



- Lift and remove the bottom cover.

### Step 4 — Antenna Plate




- Remove the following TR6 screws from the antenna plate:
  - Three 4.1 mm screws
  - Three 1.9 mm screws



## Step 5




 Do not completely remove the antenna plate; it is still connected to the Mac Mini by an antenna cable.

- With the I/O ports facing you, flip the antenna plate to the right to allow access to the antenna cable connector.

## Step 6



- Remove the single 3.4 mm T6 screw and washer from the antenna cable.
-  Be careful not to lose the washer when removing the screw.

## Step 7



- Use the point of a spudger to lift the antenna connector straight up off its socket on the airport card.

## Step 8



- Carefully pull the antenna cable out from the gap between the power supply and case.

## Step 9



- Remove the antenna plate from the Mac Mini.

To reassemble your device, follow these instructions in reverse order.

This document was last generated on 2017-06-16 06:30:35 PM.